

PURPOSE of the ARCADIAN is to act as a user-dominated forum for the dissemination of material having to do with the Bally/AstroVision Arcade cum computer. We include programs, operational hints, tutorials, and hardware items of value. The underlying reason for the paper is to help us all understand how and why the machine operates the way it does. We can then make it operate the way we want it to and expand its usefulness.

HISTORY in a nutshell - The Chicago mail order house of JS&A advertised the Bally system in popular magazines in late 1977, and a number of us bought the unit. There were lots of promises of expansion capability and actual hardware to be available in mid-1978. Delivery was poor, some of the promised material never did show up. The Basic cartridge did appear and I started this paper in November, 1978. I got tired of waiting for the Add-On memory expansion and was about to contract to get one made for us, when the Fidelity Electronics purchase became imminent. We took a second look and opted out, because there was no way we could compete with a factory product. We started to look at smaller projects, and eventually the expansions called 'Blue Ram' and 'Viper' became available. AstroVision finally took over the Bally Consumer Products Div. product, and is now aggressively moving ahead with new videocades and the AddUnder expansion unit.

TECHNICAL ASPECTS of this paper include the fact that all typing is done on an Apple, using the Super Text word processor system, and the output is printed on a Comprint 9125 electrostatic printer. Programs are printed using the Arcade as the driver, using the *PRINT command and a tap from the cassette interface. A minor inconvenience is that the printer does not have a divide sign, a multiply sign, or a right arrow - instead, it prints out a lower case letter, as follows:

a = right arrow → b = multiply * c = divide ÷

CALIFORNIA HERE I COME! is being heard around the halls of AstroVision! Yes, they are moving their offices to a small town near Sacramento, and will have a second production facility there. The move is taking place about the time you will be receiving this. The new address will be 11167 Trade Center Drive, Suite D, Rancho Cordoba, CA 95670.

ASTROVISION BASIC FEATURES: EDITOR

Editing of programs is now considerably easier. The operation is: Type the line number of the line to be corrected. Press PAUSE repeatedly to recall each individual entry in the line, one by one. Use ERASE to back up (and therefore eliminate) an entry, allowing the typing in of additional or replacement entries.

You can continue to PAUSE until the entire line is shown, and one more entry will act as the GO command. As a short cut, if you make a change in the beginning of a long line, instead of using PAUSE repeatedly to get to the end of the line, use WORDS SPACE to enter the entire corrected line.

Utilization: After entering a taped program, I LIST the program and watch for ????. Mark down the line numbers where these appear, and when the whole program has been listed, I go back to correct each line. List the single line using LIST nnn,1 where nnn is the line number (the comma and 1 tell the machine to just list one line). Then I look to see where the ??? tells me the problem is, use the PAUSE control, etc., as described above to make the corrections, and finally re-list the line to see that it is correct.

This page is written for the new ARCADIAN reader to give him a very short updating to today's status.

WHAT HAVE I BOUGHT???

The Arcade machine that you have contains four built-in programs as described in the literature that came with the machine, and it will accept Videocades in the game slot for other games, as produced by AstroVision/Bally. One of these Videocades is entitled "Basic", and insertion of this cartridge will allow you to access the Z-80 microprocessor located inside the machine, and that is what we are all about. The machine contains three custom circuits, not available in any other TV game, that help the Z-80 perform. These special circuits are enclosed in three integrated circuit chips called DATA, INPUT/OUTPUT, and ADDRESS. Also included is a memory consisting of approximately 4000 bytes of Random Access Memory (RAM), and 8000 bytes of Read Only Memory (ROM). When you insert the Basic cartridge, you can personally enter a program of up to 1800 bytes into the 4000 byte RAM. The Basic is derived from "Palo Alto Tiny Basic" written by Dr. L. Wang a number of years ago. A listing and discussion of this language is contained in Volume One of "Dr. Dobbs' Journal of Computer Calisthenics and Orthodontia" (Still available at some of the bigger computer outlets.) We can supply a listing with remarks of both the Bally Basic and the AstroVision Basic. Both of these Basics were written by Jay Fenton.

As mentioned above, the largest program that can be entered into the Arcade is 1800 bytes. While some clever program entries have been made to utilize this space efficiently, it is woefully small for any serious programming. To alleviate that problem, three avenues of enlargement are available:

ooo 1. The AstroVision Add Under. This item is currently in a pre-production prototype construction phase. That is, all the critical design parameters have been set and some hand-wired units are being built to test the concept. Meanwhile, the printed circuit board is being laid out for the production version. These prototypes will be available for show/operation at the Consumer Electronics Show (CES) early next year (where most new products are shown to wholesalers). By that time the production system should be moving along well enough so that hardware will be available by February or March for deliveries to start. We shall see. The Add Under will have enough memory for any reasonable program, and a new, different, language called ZGRASS. Its projected cost is \$600.

ooo 2. The Perkins Engineering "Blue Ram". This memory addition allows you to expand your programs by 4000 bytes. It plugs directly onto the 50-pin connector at the back of the Arcade, and has a separate power supply. In addition to providing raw memory for programming, numerous 'extras' are included or available to enhance its operation. A keyboard can be attached, for example, and a new language cartridge was just announced. 1004 Pleasant Ave., Boyne City, MI, 49712

ooo 3. Alternative Engineering produces the "Viper System", which has a modular approach to memory expansion. A large box contains a power supply and one (Viper 1) or more (Viper 5 or 10) memory cards (each card has about 16000 bytes). The Arcade sits on top of the Viper box and is connected by a short cable using the 50-pin connector at the rear. A keyboard is available as an extra. The Viper package includes a free copy of the Extended Basic language on tape. P.O. Box 128, Gardiner, ME 04345

Author Steve Walters has sent us a variation and explanation of the loading method he suggests for his program that was listed in the last issue, p.126.

The technique used to load the HALLOWEEN GRAPHICS program involves the direct mode (i.e., no line numbers used). A general explanation was printed in the ARCADIAN in Vol.3, No. 2, p. 20-21 (Dec., 1980) with a correction added in Vol.3, No. 3, p. 31 (Jan., 1981).

For the HALLOWEEN GRAPHICS program, the specific tape-loading procedure is as follows, after you have entered the program (ARCADIAN p. 126) in the computer:

1. enter the following in direct mode (no line number):

```
:PRINT; TV=0; TV=1; PRINT; PRINT ".HALLOWEEN GRAPHICS";  
PRINT ".BY S. WALTERS 10/80"; PRINT; LIST; PRINT;  
PRINT ".STANDBY FOR"; PRINT ":RETURN; :INPUT 2"
```

Do not press GO yet. Turn your tape recorder on "record" to record the program, then press GO.

You will see ?? for the input code, then the title, then the program list. When you see the last item (:RETURN; :INPUT 2) appear on the screen, immediately turn off the tape recorder, but do not rewind the tape.

2. We will now add the data trailer to the tape. Clear the computer memory, then enter LINES 10 thru 40 on ARCADIAN page 127.

Then in direct mode enter :PRINT; RUN but do not press GO yet. Turn your tape recorder on "record" to record the data, then press GO.

Again you will see ?? for the input code, then the data print on the screen, and then the last item (:RETURN; RUN). Turn the tape recorder off, rewind, and clear the computer memory.

3. The tape is now ready to load and will run automatically when input is completed. Load the tape into the computer using :INPUT 1 since the TV input code "1" was used.

The actual input operation involves the following for the computer:

:INPUT 1 opens the input port, and the computer then responds to the input code 1 by inputting the title (which is ignored by the computer since the period precedes the characters) and the program. the :RETURN instruction then closes the input port, and the :INPUT 2 reopens the port for an input code 2. This eliminates the junk which results if the tape is simply stopped and restarted for the two taping steps.

The input code 2 causes the computer to input the data, :RETURN then closes the input port and RUN causes the program to start automatically at the end of the loading.

Ad:

*** BLUE RAM SUPER EXTENDED BASIC *** FOR USE WITH THE BLUE RAM AND ITS ACCESSORIES. THIS LANGUAGE COMES IN A NORMAL CARTRIDGE AND HAS ALL OF THE FEATURES OF THE STANDARD BALLY BASIC -PLUS- ALL OF THESE ADDITIONAL FEATURES BY JAY FENTON AND (*)PERKINS ENGINEERING:

- | | |
|------------------------------------|--|
| - 4 COLORS ON THE SCREEN AT ONCE | - BUILT-IN DRIVER FOR THE BR KEYBOARD* |
| - FASTER OVERALL PROGRAM EXECUTION | - BUILT-IN DRIVER FOR THE BR PRINTER* |
| - 5 ADDITIONAL GRAPHICS COMMANDS | - FULL SOUND EFFECTS / MUSIC DRIVER* |
| - "WINDOWED" GRAPHICS AND TEXT | - 300 AND 2000 BAUD TAPE INTERFACES* |
| - 2 CHARACTER FONTS (5X7 AND 3X5) | - FULL BOOLEAN OPERATIONS* |
| - CHANGEABLE PRINT NUMBER BASE | - NEGATE OPERATOR* |
| - "TRACE" PROGRAM DEBUG AID | - VERSATILE PROGRAM LINE EDITOR* |
| - LARGER PROGRAM AREA (3100 BYTES) | - USER EXTENSIBLE COMMAND LINKAGE* |
| - 14 NEW TWO-LETTER VARIABLES | - EXTENDED GOTO AND GOSUB FORMATS* |
| - 3 ADDITIONAL DATA SET COMMANDS | |
| - PROGRAM "BOMB" RECOVERY* | - 8 MODES CONTROLLED BY MODE FLAGS* |
| - FASTER MULTIPLY AND DIVIDE* | - 5 SERVICE LINKAGES IN RAM* |

THIS CARTRIDGE COME COMPLETE WITH 2000 BAUD INTERFACE CABLE AND DOCUMENTATION DEFINING THE NEW LANGUAGE FORMATS FOR \$49.95 FROM PERKINS ENGINEERING

1004 PLEASANT AVE.

BOYNE CITY, MICHIGAN 49712. (616) 582-9832

ARCADIAN

This program is Nuclear Math, discussed on page 8.

```

1 L=1;Q=0;S=1;T=80;&(9)=43;BC=248;FC=92;NT=0;GOTO 80
2 E=RND (10)-1;F=RND (10)-1;RETURN
3 E=RND (90)+9;F=RND (90)+9;RETURN
4 E=RND (900)+99;F=RND (900)+99;RETURN
5 E=RND (6384)+9999;F=RND (6384)+9999;RETURN
6 E=RND (22768)+9999;F=RND (22768)+9999;RETURN
7 E=RND (181);F=RND (181);RETURN
8 E=RND (3);F=RND (3);RETURN
9 F=RND (20)65;E=F6RND (10);RETURN
10 F=RND (9);E=F6RND (10);RETURN
11 F=RND (9);E=F6RND (100);RETURN
12 F=RND (999);E=RND (32)6F;RETURN
13 CX=27;CY=-16;RETURN
15 GOSUB 13;PRINT "SORRY!";FOR A=1TO 250;NEXT A;T=T+5;GOSUB 13;PRINT " ";
RETURN
16 GOSUB M;BOX 29,-14,80,40,2;RETURN
20 L=Sc5+1;IF L<1L=1
22 IF QcS X=RM;IF Q#SIF Qc(Q-S)IF X>RM-1L=L-1
25 IF L<1L=1
26 IF L>4L=4
27 RETURN
28 CX=34;CY=0;NT=0;PRINT #1,E;CX=20;CY=-8;TV=K;CX=34;CY=-8;PRINT #1,F;BOX 40,-
13,50,1,1;CX=22;CY=-20;INPUT "?G;Q=Q+1;RETURN
29 CX=27;PRINT "CORRECT!";T=T-2;S=S+1;RETURN
30 BOX -52,-3,1,59,2;FOR Z=40TO T;NT=2;MU=Z;BOX -52,Z-72,1,1,1;NEXT Z;RETURN
32 GOSUB P;IF G=EbFGOSUB R;RETURN
33 RETURN
34 IF (T<41)+(T>99)GOTO Y
35 RETURN
40 FOR A=-31TO 21STEP 10;CY=A;PRINT #0,B;B=B+10;NEXT A;RETURN
80 CLEAR ;CY=0;PRINT "INPUT + - b c?";K=KP;N=Kb10
90 NT=0;CLEAR ;BOX -45,0,44,79,1;BOX -45,0,42,77,3;BOX -45,0,40,75,1;BOX -45,0
,36,71,3;BOX -52,29,7,6,1;BOX -52,29,5,4,3
100 BOX -52,-3,3,58,1;BOX -52,-3,1,59,3;FOR A=-31TO 26STEP 2;BOX -50,A,1,1,1;NE
XT A;FOR A=-31TO 21STEP 10;BOX -49,A,1,1,1;CX=-43
110 CY=A;PRINT #1,A+71;NEXT A;&(0)=0;&(1)=0;&(2)=7;&(3)=7;&(9)=18;GOTO N
430 GOSUB C;GOSUB L+1;GOSUB P;IF G=E+FGOSUB R
432 GOSUB 16;IF G#E+FGOSUB 15
434 GOSUB 0;GOTO N
450 GOSUB C
452 IF L<4GOSUB L+1;IF E>FGOSUB P;GOTO U
455 IF L=4GOSUB 6;IF E>FGOSUB P;GOTO U
460 GOTO 452
470 IF G=E-FGOSUB R
480 GOSUB 16;IF G#E-FGOSUB 15
490 GOSUB 0;GOTO N
980 GOSUB C
982 IF (L=2)+(L=3)GOSUB L;GOSUB W
984 IF L=1GOSUB 8;GOSUB W
986 IF L=4GOSUB 7;GOSUB W
987 GOSUB 16;IF G#EbFGOSUB 15
989 GOSUB 0;GOTO N
990 GOSUB C
992 GOSUB L+8;GOSUB P;IF G=EcFGOSUB R
994 GOSUB 16;IF G#EcFGOSUB 15
995 GOSUB 0;GOTO N
1000 &(10)=0;CLEAR ;B=35;FOR A=0TO 50STEP -3;B=B-4;BOX -35,B+8,A,4,1;BOX -35,-B
-B,A,4,1;BOX 35,B-8,A,4,1;BOX 35,-B-8,A,4,1;NEXT A
1010 &(9)=43;FOR A=0TO 180;&(10)=A;NEXT A;IF T>99GOTO 1050
1030 GOTO 1100
1050 B=0;&(16)=RND (5)+250;&(17)=RND (5)+250;&(18)=RND (5)+130;&(19)=RND (5)+58;
&(21)=255;&(22)=255
1060 &(23)=255;FOR A=1TO 80;MU=A;BC=Ab3;B=B+2;BOX 0,0,B,B,3;NEXT A;FOR A=16TO 23
;&(A)=0;NEXT A;GOTO 1110
1100 CX=-36;CY=0;PRINT "PLANT SAVED!";FOR A=1TO 30;FOR D=1TO 150;NEXT D;BC=RND
(32)68;FC=BC+4+RND (32)68;NEXT A
1105 CY=-8;PRINT "YOU GOT ",#1,S-1," OUT OF ",Q,"!!!
1108 FOR A=1TO 500;NEXT A
1110 PRINT "TO PLAY AGAIN PRESS A KEY";IF KPRUN
>

```

Michigan User Group meeting on
Nov 22, in Northville. Call Don
Gladden (address below) or 313-
437-3984 for details.

Don Gladden
59400 Nine Mile Road
South Lyon, MI 48178

New User Group in Peoria
Gerry Thatcher 309-383-4238
Bob Walker 309-745-8225

4D2 is an interesting graphics program that has a number of subtleties, made up by Rusty Blommaert and Dale Smith.

George Moses added lines 3000 and 3010 as a tool for getting the string variables loaded onto tape once you have entered them into the computer, as follows:

Enter the entire program, down through line 3010, then RUN it. The program will first review the contents of @ (1) /because of line 2400/, and since the contents are now 0, it will start the process of asking you to enter the string variables, 0 through 87. Enter these from the list on the right. When through, RUN the program again. This time, when the program looks at @ (1), it will see the desired 8693, and will jump to line 2450 and continue. Now, to load the program on tape, and save all those strings you just finished loading, HALT the program while it is running, start your tape recorder on RECORD, and enter GOTO 3000. You will see some strange activity as the entire program is loaded at the top of the screen only - have no fear, its ok.



```

10 GOTO 2400
20 XY=0;LINE X,Y,3
30 IF Y XY=0;LINE X,-Y,3
40 IF XIF Y XY=0;LINE -X,-Y,3
50 IF X XY=0;LINE -X,Y,3
60 RETURN
70 CALL20078
80 CALL20078
90 IF TR(1)=0RETURN
100 &(9)=44
110 :RETURN
120 CLEAR
130 CALL1532
140 &(10)=176
160 NT=1
170 GOSUB 2000
180 STOP
200 FOR X=3TO 79STEP 2
210 BOX 0,0,X,X,3
220 NEXT X
230 GOTO 70
300 FOR Y=79TO 3STEP -2
310 BOX 0,0,Y+Y-1,Y,3
320 NEXT Y
330 GOTO 70
500 FOR Y=0TO 40STEP 10
510 FOR X=5TO 75STEP 10
520 GOSUB 20
530 NEXT X
540 NEXT Y
550 GOTO 70
700 FOR Y=0TO 39
710 X=78-2bY
720 GOSUB 20
730 NEXT Y
740 GOTO 70
900 RETURN
1100 FOR X=0TO 79
1110 Y=39-Xc2
1120 GOSUB 20
1130 NEXT X
1140 GOTO 70
1300 X=79
1310 FOR Y=0TO 42
1320 GOSUB 20
1330 NEXT Y
1340 GOTO 70
1500 RETURN
1700 Y=42
1710 FOR X=0TO 79
1720 GOSUB 20
1730 NEXT X
1740 GOTO 70
2000 F=21024;G=19494;H=00;RETURN
2010 F=20303;G=21328;H=33;RETURN
2020 F=13313;G=12868;H=00;RETURN
2030 F=16706;G=19532;H=89;RETURN
2040 F=21313;G=21076;H=79;RETURN

```

```

2050 F=16706;G=18771;H=67;RETURN
2060 F=17952;G=20053;H=32;RETURN
2070 F=16711;G=17741;H=83;RETURN
2080 F=21837;G=18771;H=67;RETURN
2090 F=22305;G=22351;H=33;RETURN
2100 F=17736;G=19532;H=79;RETURN
2110 F=16928;G=17753;H=32;RETURN
2200 FOR Z=1TO 32767
2210 W=Zc9
2220 GOSUB 2030+RMb10
2230 W=Zc2
2240 IF RM=0GOSUB 200
2250 FOR V=3TO 17STEP 2
2260 W=ZcV
2270 IF RM=0GOSUB Vb100
2280 NEXT V
2290 NEXT Z
2300 GOTO 2200
2399 .SET-UP SECTION:
2400 IF @ (1)=8693GOTO 2450
2410 FOR R=0TO 87
2420 PRINT R,
2430 INPUT "*"@ (R)
2440 NEXT R
2450 :RETURN
2460 CLEAR
2470 :INPUT
2480 CALL1532
2490 &(9)=44
2500 &(10)=172
2510 A=-43;B=1845;C=-22499
2520 D=20088;E=-13871
2530 GOSUB 2020
2540 CALL20078
2550 FOR R=0TO 87
2560 %(2bR+19824)=@ (R)
2570 FC=Rb8-696
2580 NEXT R
2590 J=8438;K=19824
2600 L=16115;M=-4786
2610 N=15943;O=-11390
2620 P=-1267;Q=201
2630 CALL20078
2640 CALL20100
2650 &(9)=20
2660 GOTO 2200

```

| | | | |
|-----|--------|-----|--------|
| 0= | -6715 | 45= | -767 |
| 1= | 8693 | 46= | 11263 |
| 2= | 19998 | 47= | 2423 |
| 3= | -4090 | 48= | 16582 |
| 4= | 7387 | 49= | 11127 |
| 5= | -25429 | 50= | 2423 |
| 6= | 3855 | 51= | -32570 |
| 7= | 3855 | 52= | 11127 |
| 8= | 20284 | 53= | 2423 |
| 9= | -20290 | 54= | -16186 |
| 10= | 11127 | 55= | 11127 |
| 11= | 12517 | 56= | 2423 |
| 12= | -2807 | 57= | 6145 |
| 13= | -14722 | 58= | -4856 |
| 14= | 30472 | 59= | -7749 |
| 15= | 58 | 60= | 7994 |
| 16= | -3762 | 61= | -14770 |
| 17= | -24473 | 62= | 12408 |
| 18= | 1824 | 63= | 15878 |
| 19= | -25542 | 64= | 332 |
| 20= | 12878 | 65= | -8 |
| 21= | 19975 | 66= | 12809 |
| 22= | 4015 | 67= | 19999 |
| 23= | 3855 | 68= | 4051 |
| 24= | 28431 | 69= | 2817 |
| 25= | -14724 | 70= | -4856 |
| 26= | -24491 | 71= | -3653 |
| 27= | 1824 | 72= | -15903 |
| 28= | -25030 | 73= | -13829 |
| 29= | 12878 | 74= | 30451 |
| 30= | 19976 | 75= | 64 |
| 31= | -19025 | 76= | 0 |
| 32= | 3122 | 77= | 1 |
| 33= | 31822 | 78= | 0 |
| 34= | 21974 | 79= | 0 |
| 35= | 8352 | 80= | 0 |
| 36= | 14855 | 81= | 0 |
| 37= | 20122 | 82= | 0 |
| 38= | 2354 | 83= | 0 |
| 39= | -20658 | 84= | 0 |
| 40= | 3855 | 85= | 0 |
| 41= | 3855 | 86= | -256 |
| 42= | 2866 | 87= | 19456 |
| 43= | -7858 | | |
| 44= | 32485 | | |

Rusty Blommaert
2901 Willens Dr. #6
Melrose Park, IL 60164

```

3000 A=-24576;B=%(20050)+176;NT=1::PRINT ;CLEAR ;PRINT #1,"A=-24576;B=",B,";FOR
N=ATO B;%(N)=KP;NEXT N;%(20050)=B-176;RETURN ;RUN
3010 FOR N=ATO B;CY=40;TV=%(N);NEXT N;RETURN

```

ARCADIAN


```

1 .
3 .CODER-DECODER
5 .ED GROEBE
6 CLEAR
7 BC=8;FC=7
9 PRINT "AT END OF MESSAGE KEY IN $";PRINT ;PRINT
10 PRINT "KEY 1(CODE) OR 2(DECODE)"
15 PRINT
20 M=KP;IF (M>50)GOTO 20
30 TV=M;IF M=50M=-1
35 PRINT ;IF M=49M=1;GOSUB 550
38 PRINT
40 PRINT "ENTER MESSAGE"
45 PRINT
50 FOR Z=1TO 284
60 IF Z<1Z=1
70 @(Z)=KP
80 IF @(Z)=36GOTO 200
90 IF @(Z)=31GOTO 400
100 TV=@(Z)
110 NEXT Z
200 PRINT ;E=Z-1
210 FOR Z=1TO E
220 IF M=-1GOSUB 490
230 IF @(Z)<78S=1
240 IF @(Z)<58S=0
250 IF @(Z)>77S=-1
260 @(Z)=@(Z)+(Sb13)
270 IF M=1GOSUB 490
280 TV=@(Z)
290 NEXT Z
295 IF M=-1GOTO 600
298 PRINT ;PRINT
300 PRINT "WANT IT DECODED? KEY 2"
310 M=KP;IF M=50M=-1;GOTO 200
320 GOTO 310
400 IF CX=-77CY=CY+8;Z=Z-26;BOX 0,CY,160,8,2;GOTO 60
410 CX=CX-6;BOX CX,CY,6,8,2;Z=Z-1;GOTO 60
490 IF @(Z)<58RETURN
500 N=(Z-(Zc10)b10)
510 IF N>7N=7
520 @(Z)=@(Z)-NbM
530 RETURN
550 PRINT "USE LETTERS & NUMBERS ONLY";RETURN
600 IF KPRUN

```

Ed Groebe
12046 Flambeal Drive
Palos Heights, IL 60463

—EDGE— SOFTWARE



| | | | | | | | |
|---|---|---|---|---|---|---|---|
| 1 | 2 | 3 | 4 | - | - | - | - |
| 4 | 2 | 1 | 3 | + | - | - | - |
| 4 | 1 | 2 | 3 | + | + | - | - |
| 1 | 2 | 4 | 3 | + | + | - | - |
| 2 | 1 | 4 | 3 | + | + | + | + |

1. DOTS

2. MASTERMIND

ORDER TAPE #2

FOR \$10.95

EDGE

12046 FLAMBEAU
PALOS HTS, ILL
60463

—EDGE—

Ads

Bowling Secretary program -- calculates and stores averages, handicaps, games bowled, and total pins for entire bowling league. Sold as witten for \$6.95, or custom written for your league (need bowler's names, team numbers and handicapping info. (pct. used)) for \$12.95 Don Gladden 59400 Nine Mile, South Lyon, MI 48178 (313) 437-3984

SFP has one cassette interface, orig. carton, for \$29.95., Also four original Bally Basic w/orig. carton at \$24.95 each. NEWLY released videocades - send for free price list with ARCADIAN discount. Revolving cassette rack at \$5.95 hold 20 videocades in cases, or 32 without cases. CA add 6% tax. SFP D-A, 1064 N. Alta, Dinuba, CA, (209)- 591-0555

SUPER SOFTWARE now offers 10 complete sets of programs specifically for the Bally Arcade. We also carry the complete Bally/Astrovision line of accessories for the Arcade. All software orders are being shipped within 48 hours for speedyservice. Please write for our free six-page catalog. Super Software, Box 702, Plainfield, NJ 07061-0702

Color Organ/Light Show: Interface Bally to any Stereo Speakers, creating New Visual/Musical Forms.

Interface unit with Cassette Demo. & Instructions + Tutorial..\$39.95 Create your own Art.

24 games Available. All utilise the special Graphics.,.....Colors and Sounds that the Bally is famous for and employ maximum memory. Any Two (2) games on Cassett, with documentation \$12.95

STEREO
COLOR ORGAN
ON YOUR TV
INTERFACES WITH
BALLY ARCADE
ASTROVISION

ALL COLORS
BRILLIANT DISPLAY

ALL Programs now
Available in new
Astrovision Basic

Write for FREE
pictured Cat-
alog.


Coyote-Roadrunner Race
The Mummys Treasure
Ayatollah Dart Board
3-D Tic Tac Toe
Target (Trio of games)
** River City Gambler
Fox and the Hare
Galactic War 2002
Sink the U-Boat
Rescue Air Drop
Kill The Vulcan
Search & Destroy
Light Show Program #2
(Use with interface)
Phantom Star Fight 2003

Air Raid
Crazy Ball
Bombardier
Mission Imposs.
Space Quest 2001
Atom Smasher
Star Base 2000
The Black Lagoon
Space Checkers
** Claim Jumpers
** 1 to 5 Players
includes com-
puter too.
Super Sleuth


Visa & Master Charge Accepted.

IDENTIFY IF BALLY
OR ASTROVISION
BASIC


The Following Graphic Pictures are True Representations of the games we sell




Target
1 to 4 players




River City Gambler
1 to 5 players **




3-D Tic Tac Toe
2 players



Phantom Star Fighters 2003
2 players



Space Checkers
2 players



Claim Jumper
1 to 5 players **

CONTEST ENTRIES this month are three:

o 4D2, which is a purely graphics presentation that gives you something soothing to look at and admire. While the program appears random, I am told that it is a giant loop that starts again in about three days. There is a lot of machine language code in it, and it runs in Bally Basic only. The authors are working on an AstroVision Basic version.

o Nuclear Math is an arithmetic training game that asks the operator to perform math problems. Correct answers will cool the nuclear reactor thermometer, while incorrect ones will drive the temperature up to a calamity.

o Code-Decode is a 'utility' program that is used for a specific purpose. The program will automatically encrypt a message using some special rules. Only another Arcade with the same program will be able to decrypt the message. Note that this is not a substitution type of code, but real encryption, where a single letter does not always have the same meaning.

BLUE RAM EXTENDED BASIC cartridges are now being delivered. See their ad for details of the cartridge. Attach the Blue Ram memory addition, and then insert the Blue Ram cartridge. The screen goes blue and the title (as printed above) comes up. Then the cursor shows up in the small font format, as does anything entered. By using CF=LARGE, the font size changes to the standard. If you have the Blue Ram Keyboard, it can be attached, and all entries made through it. The ROM cartridge contains the keyboard operating system, eliminating the old tape entry method.. The keypad works as well. We'll be including some tutorials and programs for the Ram's new Basic cartridge very soon.

Advertisements - The two or three-line items on the last page are free to subscribers until they get overwhelming. Small display ads up to 1/4 page are also free. Send for rates on half-page or larger ads.

Programs in the ARCADIAN are entirely the work of subscribers. Programs should be sent on a tape (if you have the Bally Basic, I prefer it that way), accompanied by a listing (which may be hand written, as long as it is legible - we only use it in case the tape fails), and a complete description as to operation, etc., of the program. Submittal of a program is considered to be a donation for the common betterment and education of all, and no payment is made. We do, however, have a monthly contest. Any program submitted to the contest requires a statement that the program is an original work and not a copy of an existing program. Contestants will vie for a \$100 prize, supplied by the ARCADIAN. We have a 5-man rotating judging panel who use their own criteria to decide between contestants. There must be at least two entrants for the contest to operate. At the end of the Volume year, we go back and select 10 of the most popular programs from the entire stock (except contest winners), and make up a tape to be sold by dealers and directly. Sales of these "Best of ARCADIAN, 198x" programs will result in royalty payments to the authors.

PLEASANT DILEMMA is caused by having both the Blue Ram and Viper extended memory systems here, and having to pick and choose which one to plug into the Arcade. Well, there are two Arcades here now, each with an extended memory and so we will be able to try out both systems in parallel, entering programs into both to check operation and compatibility.

The Bit Fiddlers will be presenting a cartridge that will allow machine code programming directly from the keyboard later this month. I expect a full ad in the next issue.

*When you're through
playing "Space Invaders" . . .*

**PLAY "SILENT NIGHT"
on your Bally Arcade!**

**PRESENTING 3-PART
ARCADE CHRISTMAS MUSIC**



A 60 minute cassette tape
that programs your Arcade
to play 27 beautiful
Christmas Carols in 3-part
harmony, some with vibrato.
Close your eyes and listen
and you'll think someone's
playing an organ!

**Just push: INPUT-GO and they all
play consecutively.**

All 27 programs on one tape \$9⁵⁰



Send check or money order to:

GEORGE MOSES CO.

**110 E. North St., Brighton, MI 48116
(313) 227-1575**

NEW 3 VOICE MUSIC ASSEMBLER FEATURING NO REM STATEMENTS!

BY GEORGE MOSES

In May, 1980 The Arcadian published an introduction of three-voice music programming to Bally Basic aficionados. I received this program, previously thought impossible in Basic, from its creator, Brett Bilbrey of Dearborn, Michigan and spent about 3 months refining it to make it more easily used and understood by Arcadian Subscribers.

This program opened the door to a new realm of creative expression with my Arcade and I spent hundreds of hours programming sheet music. Along the way, I made changes in the program to clean up the timing problems inherent in the many counting loops and IF statements of the original program. That whole program has now faded into obsolescence as new discoveries have initiated a complete overhaul of the music assembly methods used in the past. Somewhere you have to quit changing a program and say, finally, "This is the way it's gonna be!" That's the program we've included here.

Shortly before completing it, I received a letter from Jim Dunson in Pensacola, Florida that led to the biggest and final revision, the elimination of REM (.) statements for storing the poked data. Jim discovered that you can poke data into the text memory area beyond %(20050), which is the memory address of the SZ indicator at the end of your program. If you command the computer to PRINT %(20050) GO it will print out the memory address of the end of the program. The advantage of this method is that you no longer have to type in those long REM statements at the beginning of the program to store your data. However, you need to use a new method to write the data to tape as your computer won't list the data beyond %(20050). So, I've included a print-to-tape subroutine beginning on line 15 and created for this purpose by Dave Ibach of Northville, Michigan.

THE MUSIC PROGRAM BY GEORGE MOSES

With the help of Brett Bilbrey, Jim Dunson & Dave Ibach

```

1 :RETURN ;NT=0;K=127;L=255;M=256;GOTO 3
2 FOR C=A-1 TO E-2 STEP 3;%(17)=%(C)+M
  +K;%(18)=%(C+1)+M+K;%(19)=%(C+2)+M
  +K;FOR D=1 TO T;NEXT D;NEXT C;RETURN
3 NT=0;IF B=0B=%(20050)+6;%(B-1)=1;E=B
4 FOR N=0 TO 2;PRINT #1,E;INPUT "J;IF J>M
  INPUT "START AT?"A;GOTO 6
5 J=J-K;J=J+L*(J<0);@N=J;NEXT N;NT=1;
  INPUT "DURATION?"D;FOR N=1 TO D;FOR A=
  0 TO 2;%(E+A)=%(E+A)+M*M+@A;NEXT A;
  E=E+3;NEXT N;RUN
6 CLEAR ;BC=RND (32)*8+2;FC=BC+4;NT=0;
  K=127;M=256
7 T=15;%(16)=49;%(21)=12;%(22)=204
8 GOSUB 2
9 FOR F=22 TO 16 STEP -1;%(F)=0;NEXT F;CY=0;
  PRINT "[1]REPLAY";PRINT "[2]INPUT ";PRINT "[3]
  CHANGE";PRINT "[4]PRINT TO TAPE
10 R=KP;IF R=49 GOTO 6
11 IF R=50 RUN
12 IF R=51 INPUT "ADDRESS OF CHORD?"E;RUN
13 IF R=52 GOTO 15
14 GOTO 10
15 H=-24576;NT=1;:PRINT ;CLEAR ;PRINT "H
  ="#,H,"E=","E","B=","B","A="B;
  FOR N=H TO E;%(N)=KP;NEXT N;%(20050)=
  B-6;:RETURN ;GOTO 6
16 FOR N=H TO E;CY=40;TV=%(N);NEXT N;
  :RETURN
  
```

SAMPLE DURATION CHART

(If song's shortest note is 16th note)

| NOTE | INPUT |
|---------|-------|
| 16th | 1 |
| 8th | 2 |
| Quarter | 4 |
| Half | 8 |
| Whole | 16 |

FIG. 1

Song's shortest note is the reference point receiving a duration of 1. Then, each advance in note category doubles in duration value.

After you've input the program, record it on tape for safekeeping. Then press RUN and GO. The screen will clear and you'll see the beginning address of the first chord at the top of the screen. Using the notes from your sheet music converted to the numbers on the note chart (FIG 2), input the 3 notes in your first chord. Then the computer will ask for the duration of the chord. (See FIG. 1). The duration of a chord is determined by the shortest note in the chord. If all three notes are of identical length there's no problem. Any notes of longer duration than the shortest sounding note should be carried into the next chord and even into the chords following, if necessary, until their total duration has been accounted for. When carrying a note through two or more chords input it into the same voice and it will continue to play as one continuous, but longer sounding note. To play the same note in successive staccato beats just input it into a different voice for each chord. (See FIGS. 3 & 4.)

ONE CONTINUOUS CHORD




FIG. 3

TWO DISTINCT CHORDS




FIG. 4

To illustrate FIG. 3, press WORDS RUN GO to get the program running. Input the first chord thusly:

```

26 GO
39 GO
50 GO
  
```

4 GO Allow an interval of time after the Duration entry for the computer to perform the pokes to memory. Then go to the next chord and repeat the process. To hear the two chords type: 333 GO and the computer will ask "START AT?" Type: B GO

Listen! It's just one long, continuous chord. Now input FIG. 4. Select CHANGE from the menu. Then the computer will ask: "ADDRESS OF CHORD?" Type "B" to get back to the beginning of data storage and input FIG. 4 just as you did FIG. 3. Listen to the two chords in FIG. 4. You heard two distinct chords, didn't you? That's what happens when you switch the notes to different voices in succeeding chords. If you have less than 3 notes in a chord, or no notes at all, as in a rest, just input a zero into any voice not being used.

After you input a duration the computer will poke the entire chord into memory as many times as the duration number you selected. Then the screen will print the beginning address of the next chord. Anytime you wish to hear the music played up to the last chord you've input, just put in any number greater than 256. I like to use 333. (Don't do this when the computer is asking for a duration or that chord will be poked into memory 333 times, using 999 bytes of memory faster than you can say "OOOPS".)

Next you'll be asked for the "START" address of the music. If you want to hear the song from the beginning simply input B, which stores the memory address of the first chord. To begin listening in the middle of the song, input the memory address of the chord you want to start at. To hear it again, press the number 1. To resume inputting data where you left off press 2. To change a chord that doesn't sound right press 3. If you press 3 you'll be ask-

11

INTRODUCTORY OFFER: New ARCADE PLUS(with ASTROVISION BASIC) \$250.
Astrovision BASIC cartridge only \$45. Other cartridges 10% off.

Z-GRASS-32 ADD UNDER Unit (when available) 25% off.

** Offer good only on orders received before December 31, 1981. **

CALL or WRITE: Robert Taylor, 1555 Venus St., Merritt Is., Fla. 32952
305-453-2631 VISA or MASTERCARD accepted.

BALLY PROFESSIONAL ARCADE, NEW, with 6 controllers, Basic
w/cassette interface, 12 game carts., many audio games. Lists for \$820,
will sell for \$450. (408) 997-3063 (Cal)

Bally with Basic and cassette interface (A-1 shape) 5 factory
cartridges, 7 cassettes of skill and adventure, several from Arcadian.
Practically complete 3 years of Arcadian. \$350. K.Doughty 2344 S R 261
Newburgh, IN 47630

Bally Arcade with 6 controllers, basic, audio interface, works fine
\$200 plus most videocades at additional cost. L.Burchett, (313) 973 -1096
(Mich)

Bally Arcade, 2 hand controllers, cassette interface, Blue Ram,
Basic, programmer sampler cart., maze/tic-tac-toe cart., XY Tutorial
cart., football. Supporting software, Hacker's Guide Arcadian (since 1979)
and Cursor (since Jan 80) Best Offer. Al Zarker, 11814 Indianhead Dr.,
Austin TX 78753

Bally Arcade 2 controllers, Basic, cassette interface, Football,
Baseball, Bally Pin, Space Invader, Elem. Math, Vol 1-3 Arcadian, hacker's
guide, Service Manual PA-1. Runs great \$350 or best offer Glen Walker (916)
363-5967 (Cal)

I have a 12 year old friend that is crazy over my Bally Arcade. I am
looking for an Arcade with problems; I have the ability to fix. Send
information to Larry W. Horrall, RR#1 Box 62, Wheatland, IN, 47597

Bally Arcade with 4 controllers, Basic, Cassette Interface and 3 game
carts. Near new condition. Will include 1 year's subscription or extension in
the Arcadian. \$250/ofr. Pete (415) 591-9479

12



R. Fabris, Purposeful
3626 Morrie Dr.
San Jose, CA 95127-9990

The SOURCE TCD959

63301BRG2917H
ARTHUR BERGANTZ
2917 HEADLAND DRIVE
ST CHARLES, MO

63301